

Overview of AR-Cluster User Commands AR-Cluster User Manual

The following list is a summary of AR-Cluster commands. The upper case part of the commands is required and the lower case part of the command is optional. Thus the command **A/F** is the same as the **ANNOUNCE/FULL** command. Details for each command can be found by clicking on its link.

Announce	Announcement to all locally users
Announce/Full	Announcement to all users
Bye	Terminate the connection to the cluster
CLEAR/OSL	Remove a QSL route from the local QSL database
CONFERENCE	Enter a local conference
CONFERENCE/Full	Enter a network wide conference
DB	Built in database information
DEElete	Delete a mail message
DIRectroy	List mail messages
Dx	Enter as DX spot
Help	Command for help
List	List mail messages
Quit	Terminate the connection to the cluster
Read	Read a mail message
REPLY	Reply to a mail message
Send	Send a mail message
SEt/ANNouncements	Turn on announcements
SEt/BEep	Turn on a beep for DX and Announcement spots
SEt /DX_Announcements	Activate DX spots
SEt/DXScty	Turn on the display of the spot CTY (country)
SEt/DXSqth	Turn on the display of the spotter QTH
SEt/EMAIL	Set your Internet email address
SEt /FILTER	Set the spot filters
SEt /HEre	Let others know you are at your station
SEt /HOMenode	Set your home node
SEt /LOCAtion	Set the location (lat/lon) of your station

SEt / LOGIN_announcements	Show user logins
SEt /Name	Set your name
SEt/NOAnnouncements	Turn off announcements
SEt /NOBeep	Turn off the beep for DX and Announcements
SEt / NODX_Announcements	Turn off DX announcements
SEt/NODXScty	Turn off the display of the spot CTY (country)
SEt/NODXSqth	Turn off the display of the spotter QTH
SEt /NOHere	Indicate you are away from your station
SEt / NOLOGin_announcements	Turn off login announcements
SEt/NOTalk	Turn off the display of talk messages
SEt/ NOWWV_announcements	Turn off the display of WWV spots
SEt/NOWX_announcements	Turn off the display of weather announcements
SEt/PHONE	Set your phone number
SEt/QRA	Set the QRA for your station
SEt/QSL	Add a QSL route to the local database
SEt /QTH	Set your location (city, etc)
SEt/TAlk	Turn on the display of talk messages
SEt/WWV_announcements	Turn on the display of WWV spots
SEt/WX_announcements	Turn on the display of weather announcements
SHow/ANnounce	Show previous announcements
SHow/ARCHive	Show the files in the archive folder
SHow/BUcmaster	Show callbook information for a specified callsign
SHow/BULLEtins	Show the files in the bulletins folder
SHow/CBA	Show callbook information for a specified callsign
SHow/CLuster	Show the configuration of the cluster
SHow/Configuration	Show the users on the node
SHow/Dx	Show previous DX spots
SHow/Dx SQL	Query for past DX using SQL
SHow/EMAIL	Show a users Internet email address
SHow/FDx	Display a formatted SH/DX command

SHow/FILEs	Show the files in the files folder
SHow/FILTER	Shows the current DX spot filters
SHow/FITu	Display a formatted SH/ITU
SHow/FZOne	Display a formatted SH/ZONE
SHow/Grid	Show the MaidenHead grid locator for a station
SHow/HAM	Show callbook information for a specified callsign
SHow/Heading	Show the heading and distance to a station
SHow/HOMEnode	Show a users homenode
SHow/ITu	Show past DX based on a ITU zone
SHow/LOCation	Show the location (lat/lon) of a station
SHow/LOG	Show the node logins for a call
SHow/Muf	Show the MUF for a country
SHow/NEeds	Show the CTY needs for a station
SHow/NOdes	Displays a list of nodes in the network
SHow/Prefix	Show the prefix information for a call
Show/QRA	Show the station QRA
SHow/Qsl	Show QSL information for a call
SHow/STation	Show detail information for a call
SHow/Sun	Show the sunrise/sunset for a location
SHow/TAlk	Show past talk messages
SHow/TIme	Show the time
SHow/TIP	Show a tip about using the cluster
Show/UPTime	Shows the uptime for the node
SHow/Users	Show the users connected to the node
SHow/Version	Shows the AR-Cluster software version
SHow/WWv	Shows past WWV information
SHow/WX	Show past weather announcements
SHow/WXStation	Show data from an optional weather station
SHow/Zone	Show past DX based on a CQ zone
Talk	Talk to a station
Talk/Timestamp	Talk to a station with a timestamp
Type/ARChive	Display a file in the archive folder
Type/BULletins	Display a file in the bulletin folder
Type/FILEs	Display a file in the files folder

Wwv	Send a WWV spot to the cluster
WX	Make a local weather announcement
WX/Full	Make a weather announcement to the network